

# 95060 Series

## Sealed Ignition Switch with Integrated Connector



### Specifications

#### Contact Ratings:

10A @ 12V DC  
5A @ 24V DC  
3A @ 36V DC  
2A @ 48V DC

#### Ingress Protection:

Contacts sealed front and back to IP67 (with connector installed)

#### Hardware:

Plastic facenut and nickel-plated brass backing nut

#### Mounting Torque:

Plastic facenut: 7.376-8.85 ft-lbs (10-12 Nm)

### Description

An extensive series of ignition switches that can also be used as rotary switches. Suitable for a broad range of voltages: 10A at 12V, 5A at 24V, 3A at 36V and 2A at 48V DC. Made of rugged engineering grade plastic, these switches stand up to mechanical shock and vibration, and will not corrode or rust. This switch has an integrated Deutsch-type socket to make electrical connection quick and easy, and to exclude moisture and dust. UL-tested and recognized to SAE J259 for ignition switches. Contacts are sealed front and back to IP67 (with connector installed).

Many options available with regard to position, spring return, key boot style and marking, actuator interface and length, and anti-restart features.

### Features and Benefits

- Engineering thermoplastic construction
- Fully sealed contact area using O-rings and ultrasonic welding
- Integrated Sealed Deutsch Connector Interface
- Anti-restart and spring return options available
- Tested to SAE J259 for ignition switches
- Supplied with two matching keys, with or without boot
- Custom logo can be molded on the boot
- Multiple key codes or keyed alike available
- Key is removable only at the 'Off' position

### Web Resources

Download technical resources at: [littelfuse.com/95060](https://littelfuse.com/95060)

### Ordering Information

| PART NUMBER | POSITIONS                                                 |          |        |         |        | SPRING RETURN** | WITH KEY BOOT | WITH ANTI-RESTART |
|-------------|-----------------------------------------------------------|----------|--------|---------|--------|-----------------|---------------|-------------------|
| 95060 *     | 4                                                         | Acc      | Off    | Ign/Acc | Start  | Yes             | Yes           | No                |
| 95060-01 *  | 4                                                         | Acc      | Off    | Ign/Acc | Start  | Yes             | Yes (CH Logo) | Yes               |
| 95060-03 *  | 3                                                         | —        | Off    | Ign/Acc | Start  | Yes             | Yes (CH Logo) | No                |
| 95060-04 *  | 3                                                         | —        | Off    | Ign/Acc | Start  | Yes             | Yes (CH Logo) | Yes               |
| 95060-07 *  | 2                                                         | —        | —      | Off     | On     | No              | Yes (CH Logo) | No                |
| 95060-11    | 4                                                         | Acc      | Off    | Ign/Acc | Start  | Yes             | No            | Yes               |
| 95060-21    | 3                                                         | —        | Off    | Ign/Acc | Start  | Yes             | Yes (CH Logo) | Yes               |
| 95060-23 *  | 4                                                         | Acc      | Off    | Ign/Acc | Start  | Yes             | Yes (CH Logo) | No                |
| 95060-24    | 4                                                         | Acc      | Off    | Ign/Acc | Start  | Yes             | Yes (CH Logo) | Yes               |
| 95060-26    | 3                                                         | —        | Off    | Ign/Acc | Start  | Yes             | Yes           | No                |
| 95060-27    | 3                                                         | —        | Off    | On      | On     | No              | Yes (CH Logo) | No                |
| 95060-33    | 4                                                         | Acc      | Off    | Ign/Acc | Start  | Yes             | No            | Yes               |
| 95060-34 *  | 4                                                         | Acc      | Off    | Ign/Acc | Start  | Yes             | No            | No                |
| 95060-36    | 3                                                         | —        | Mom On | Off     | Mom On | Yes (to Off)    | No            | No                |
| 95061-04 *  | 3                                                         | —        | Off    | Ign/Acc | Start  | Yes             | No (Lever)    | Yes               |
| 95061-47    | 4                                                         | GlowPlug | Off    | Ign/Acc | Start  | Yes             | No (Lever)    | Yes               |
| 95062-30    | 3                                                         | —        | Off    | Ign/Acc | Start  | Yes             | No (D-Shaft)  | No                |
| 95060-50-BP | Same as 95060 with harness (Deutsch connector & wires)    |          |        |         |        |                 |               |                   |
| 95060-60-BP | Same as 95060-03 with harness (Deutsch connector & wires) |          |        |         |        |                 |               |                   |

\* Box and Retail Blister Pack Available


\*\* Spring Return is to Ign/Acc Position

Datasheet Replaces Hotfeed Number D-613

# 95060 Series

Sealed Ignition Switch with Integrated Connector


## Switch Dimensions



## Key Diagrams


### With Key Boot

2 Double Bitted Booted  
Keys Ringed, Black



### Without Key Boot

2 Double Bitted  
Keys Ringed



NEED KEYS FOR

**95060 Series Switches**



Key Code Ranges  
600-799

**CALL 800-255-1919**

**FUSES UNLIMITED**

Authorized Key Distributor for 95060 Switches