

# POWR-GARD FUSE

TOO, TLO, SOO & SLO SERIES  
PLUG FUSES 125 Vac • ¼-30 A



## Description

Littelfuse Plug fuses provide overcurrent protection to general purpose circuits and small motor loads. Edison-base Plug fuses (TOO and TLO series) feature metal threads similar to incandescent lamp bases.

Type S Plug fuses (SOO and SLO series) utilize a nonmetallic threaded base and must be used with Type S adapters (SAO series).

The National Electrical Code permits Edison base Plug fuses to be used for replacement purposes only. Type S fuses and adapters prevent shunting open fuses and over-fusing.

## Specifications

<b>Voltage Rating</b>	125 Vac
<b>Interrupting Rating</b>	10 kA rms symmetrical
<b>Approvals</b>	UL Listed 248-11

## Web Resources

More information: [littelfuse.com/plug](http://littelfuse.com/plug)

## Ordering Information

SERIES	AMPERAGE	CATALOG NUMBER	ORDERING NUMBER
TOO	¼/10	TOO.400	0TOO.400Z
TLO	15	TLO015	0TLO015.Z
SOO	2 ½	SOO02.5	0SOO02.5Z
SLO	30	SLO030	0SLO030.Z

### TOO Series - Dual-element time-delay Edison base fuses

AMPERE RATINGS			
¼/10	½	1	1 ¼
1 ⅝/10	2	2 ½	3 ⅔/10
3 ½	5	5 ⅝/10	6
6 ¼	7	8	10
12	15	20	25
30	—	—	25

### TLO Series - Medium time-delay Edison base fuses

AMPERE RATINGS			
15	20	25	30

### SOO Series - Dual-element time-delay Type S fuses

AMPERE RATINGS				
—	2	—	6 ¼	14
—	—	4	7	15
1 ¼	2 ½	—	8	20
1 ⅝/10	—	5	—	25
1 ⅝/10	—	—	10	—
—	3 ⅔/10	—	12	—

### SLO Series - Medium time-delay Type S fuses

AMPERE RATINGS		
20	25	30

### SAO Series - Type S fuse adapters

SAO ADAPTER	ACCEPTS FUSE RATINGS
SAO001	¼ - 1
SAO1.25	¼ - 1 ¼
SAO01.6	¼ - 1 ⅝/10
SAO03.2	1 ⅝/10 - 3 ⅔/10
SAO004	3 ½ - 4
SAO005	3 ½ - 5
SAO015	7 - 15
SAO020	20 only